

REVAMP8250

8-channel bridgeable class D power amplifier, 8 x 250W, 4ohm



This 8-channel bridgeable power amplifier is probably the most versatile class-D amplifier in the range. Combined with a pre-amplifier or matrix the REVAMP8250 can be used to create 8 zones in mono, 4 zones in stereo, even 4 bridged mono or 2 bridged stereo systems can be created. The amplifier has an intelligent variable speed cooling fan built-in to keep the unit cool at all times.

When installing the REVAMP8250, a handy input overload LED indicator on the rear and amplifier clip indicator on the front will guarantee a fast and hassle-free installation. Due to the amount of channels, limited amplifiers are needed in your project. This will save money and space, making it the ideal choice for your install.

TECHNICAL SPECIFICATIONS

dynamic output power 4 ohms in watts	8 x 350	RMS output power 4 ohms in watts	8 x 250
dynamic output power 8 ohms in watts	8 x 175	RMS output power 8 ohms in watts	8 x 125
dynamic output power bridged 8 ohms in watts	4 x 650	output power RMS bridged 8 ohms in watts	4 x 500
minimum impedance load per channel in ohms	4	minimum impedance load bridged per channel in ohms	8
power consumption (max) in watts	2200	19" (483 mm wide) rack mounting	yes
height- rack units (1U=44 mm) in U	2	height in mm	88
depth (build in) in mm	330	depth (incl front) in mm	338
power supply	115 - 230 VAC	power supply technology	switching mode power supply
output channels	8	line input balanced	8
line input unbalanced	8	channel separation	> 60 dB @ 1 kHz
power amp topology	class-D	applicable in 100V	no
applicable low impedance	yes	Net weight product (kg)	21.7

MORE PICTURES



CK Document
imaging
by Charles Kieffer Group

Tél. +352 26 380 1 Fax +352 26 380 380
sales@ck-group.lu
2, rue Léon Laval - Z.A. Am Bann
L-3372 Leudelange
ck-documentimaging.lu