

CLEVERTOUCHPRO



The **Clevertouch Pro** has a specially designed user interface, powered by Android, and written to be simple and engaging to use. Available in sizes 65", 75" and 84", Clevertouch Pro is as easy to use as a tablet.



Integrated Android OS. Purpose built operating system and intelligent user interface. Powered by Android and designed to be fast and functional with the latest specification, 2GB RAM and 16GB ROM.

Included with the Clevertouch Pro:



CleverShare Wireless Device



With the **CleverShare wireless device** you can control the **Clevertouch Pro** from anywhere in the room, without the need for any wires. Simply plug the **CleverShare** into your laptop's USB port and you can show and edit your laptop's content on the Clevertouch screen. You can instantly display your desktop and control from your computer or **Clevertouch** – your pen or finger becomes your mouse.

CLEVERTOUCHPRO

65" Clevertouch Pro

1541029



Powered by: 

Display

Diagonal size	65inch
Screen type	LED
Aspect ratio	16:9
Display area	1428.48 (h) x 803.52 (v)
Resolution	UHD 4K
Response time	8ms
Refreshing frequency	120Hz
Display colours	1.07B (10-bit)
Brightness	450 cd/m ²
Contrast ratio	1400:1
Viewing angle	178°
Life time	50,000 hrs

Video / Audio

Speaker Type	Built-in speaker
Max Output Power	2 x 10W

Connectivity

CVBS	1
VGA Input (15 pin D-Sub)	3
HDMI Input	4
PC-Audio	3
R/L (CVBS)	With video IP
VGA Output	1
Audio output earphone port	1
Coaxial digital audio output	1
USB2.0	3
USB3.0	1
WAN(RJ45)	1
RS232 Control	1

Touch System

System	Windows 7/Windows XP/Vista/Linux/Mac/Android/Wince
Sensing type	Infrared System (5 points writing and 10 point touch)
Response area	>Φ7mm
Response time	<15ms
Communication mode	Full-speed USB (driver free)
Surface protection	Toughened Glass with Level 7 of Mohs Standard
Output coordinate	32767 x 32767
Life time	Use Auto Power Control (APC) Technology; Life Time over 80,000 hrs

Android

System version	4.4 KitKat
CPU	ARM Cortex A17 Quad Core
GPU	Quad Core
RAM	2GB(DDR3)
ROM	16GB

Power

Power requirements	100V-240V AC 60/50Hz
Power consumption	250W
Power consumption in standby mode	≤0.5W

Physical Specifications

Key location and number	Front physical key, 6
Dimension W x H x D (mm)	1544 x 942 x 94
Dimension (package) W x H x D (mm)	1700 x 1100 x 215
Net weight	66kg
Gross weight	75kg
VESA (mm)	600 x 400

Accessories

AC power cable	✓ (3 metres)
Stylus pen	✓ (19, 26, 127 mm)
Remote control	✓
Application and driver disk	✓ 2
Quick start guide	✓
VGA cable	✓ (5 metres)
USB cable	✓ (5 metres)
Audio cable	✓ (5 metres)
Operation instructions	✓
WHDI transmit	✓
HDMI	✓
Clevershare	2

* Please note 10-point touch in PC mode with Windows 7/8 PC, 6-point touch in Android mode, 1-point touch with Mac OS

CK

**Document
imaging**

by Charles Kieffer Group

Tél. +352 26 380 1 Fax +352 26 380 380
sales@ck-group.lu

2, rue Léon Laval - Z.A. Am Bann
L-3372 Leudelange

ck-group.lu